


LH701A-SFP and LH702A-LC

Driver Update

Driver Installation Note - Change "Speed and Duplex" to "100 Mbps Full Duplex"

After you successfully install the driver, the LH701A-SFP or LH702A-LC will work properly for a short time. To ensure continual operation, you must change the "Speed and Duplex Property Value" as described below.


1. In Windows, navigate to the Start > Settings > Control Panel > System > Device Manager > Network Adapters menu path.



2. Select and right click the "ASIX AX88772B USB to Fast Ethernet Adapter" (the name of the chipset / manufacturer). The General tab displays the message "Windows has stopped this device because it has reported problems. (Code 43)".
3. Select "Properties" and then select the "Advanced" tab.

To continue, turn this page over...

...continued from other side of page:



4. At the "Speed and Duplex Property Value" dropdown, change the Ethernet link speed from "Auto Negotiation" to "100 Mbps Full Duplex."
5. Click the OK button.
6. Unplug and replug the LH701A-SFP or LH702A-LC. The device will now run properly.